

YAESU VX-6R QUICK REFERENCE

TX PWR:	[F/W]	[∞/TXPO]	LOCK:	[∞/LK]	1 SEC
CTCSS					LOCK ICON
SET:	[F/W]	[MODE]	DIAL	tone	"T" ICON
	[F/W]	[2(CODE)]	DIAL:	Hz	[2(CODE)]
MEMORY					
STORE:	[F/W]	1 SEC	DIAL:	CH#	[F/W]
RECALL:	VFO MODE:			[V/M]	DIAL: CH#
	MEM MODE:			CH#	[V/M]
NAME:	[F/W]	[0/SET]	NM SET		[0/SET]
ALSO FOR		DIAL	ALP/NUM		[MODE]
(BNK NM)		MISTAKE?:			[BAND]
		FINISH:			PTT
SHOW:	[F/W]	[0/SET]	NAME		[0/SET]
			ALPHA		PTT
MEMORY BANK					
ASSIGN:	[F/W]	1 SEC	[1] [1] [0] [0]	DIAL	[F/W]
REMOVE:	[F/W]	1 SEC		[∞(LK)TXPO]	
SCANNING					
	[BAND]	1 SEC	RELEASE [BAND] TO START		
SKIP:	[F/W]	[5/SKIP]	DIAL	SKIP	> STUDY
PRIORITY:	[F/W]	[5/SKIP]	DIAL	ONLY	> BLINKS
PAUSE:	[F/W]	49:RESUME	DIAL	PAUSE	TIME
APO (AUTOMATIC POWER OFF)					
	[F/W]	[0/SET]	1:APO	DIAL	PTT
WAKEUP	[F/W]	[0/SET]	72:WAKEUP		[0/SET]
			DIAL:	POLL INT	PTT
CHECKS FREQ. SELECTED WHEN TURNED OFF					
PRI CH. SET:	"MEM." MODE	[F/W]	1 SEC	DIAL	CH. #
	[BAND(SCN)BND DN]			"PRI" ICON	
DUAL WATCH:	[V/M(DW)MT]	1 SEC	CHKS "PRI" @5 S		